

# marantz®



## MM7055 - Multichannel Main Amplifier

The MM7055 is the five-channel option in this year's extended line-up of main amplifiers. Based on the technology used in the MM8003 and using the exact same chassis, it delivers a thumping 140W rms into 8 ohm to each of the channels, while the ultra-wide bandwidth current feedback technology easily handles the highest SACD frequencies – this also makes it ideal for the high definition DTS Master Audio and Dolby TrueHD formats too. The result? Totally precise tonal and image balance, speed and dynamics. And on top of all that, you also get XLR audio inputs, DC triggers and a Marantz control bus system for remote on/off. This is power and convenience to take your breath away.

### MAIN FEATURES

- 5ch power amplifier
- 5x 140W (8ohm) / 5x 170W (6ohm)
- Current Feedback circuitry
- High performance power supply
- XLR inputs
- DC Trigger control inputs

because music matters



SPECIFICATIONS	MM7055
<b>FEATURES</b>	
Channels	5
Current Feedback Topology	o
Phono EQ: Standard/Current Feedback/Constant Current Feedback	-/-/-
HDAM version	-
Power Transformer: Toroidal/El	-/o
High Grade Audio Components	o
Customised Components	o
Symmetric PCB layout	-
Aluminium extrusion heatsink	o
Copper plated chassis	-
Tri-Tone Control (Bass/Mid/Treble)	-
Balance/Bass/Treble/Loudness	-/-/-/-
<b>OTHER</b>	
Linear Drive Power Supply	o
BTL possibility	-
Bi-Amp and Multichannel option	-
Shottkey diodes	-
Input Buffer Amp (All inputs/CD only)	o/-
Seperate solid heatsinks	-
System block shielding: copper/metal/none	-/-/-
Double layer bottom plate	-
Source Direct	-
Power Amp Direct	o
Standby mode	o
<b>INPUTS/OUTPUTS</b>	
Phono Input: MM/MC	-/-
Balanced In/Out	5/-
Pre-Out/Main In	-/5
Power Amp Direct In	o
Gold Plated Chinch	-
Speaker A/B	-
Speaker terminal: Screw/Marantz/WBT	o/-/-
Number of terminals	5
Marantz remote bus	o
Remote power control (Trigger In/Out)	o
Flasher In/IR receiver In	o/-
Headphone Out	-

SPECIFICATIONS	
Power Output (8/6 Ohm RMS)	140/170 Watts
Power Output (8/6 Ohm DIN)	-
Power Output (8/6 Ohm IHF)	-
Bridged Power Output (8 Ohm RMS)	-
Frequency Response	8Hz-100kHz
Total Harmonic Distortion	0.03%
Damping Factor	100dB
Input Sensitivity: MM	-
Input Sensitivity: MC	-
Signal to Noise Ratio: MM/MC	-/-
Input Sensitivity: High level	1.2V/22kohm
Input Sensitivity: Balanced High level	2.4V/30kohm
Signal to Noise Ratio: High level	105dB
<b>GENERAL</b>	
Available colors: Gold/Silver/Black/Silver-Gold	-/-/o/-
Metal Front Panel	o
Power Consumption in W	440
Standby Consumption in W	0.4
Auto Power off	o
Detachable Power Cable	o
Remote Control	-
System Remote Function	-
Maximum Dimensions (W x D x H) in mm	440x384x184.5
Weight in kg	15.2